

# INVISILED® CLASSIC 12V and 24V

- 2W per foot
- 50,000 hours of potential life
- Temperature tolerance: -4° to 122° F
- Relative humidity: up to 95%
- Dimmable with Electronic Low Voltage (ELV) dimmer
- Combine 5', 1' and 2" sections to customize lengths
- Field cuttable every 1" for 12V and every 2" for 24V, or at the end of every run
- 12V – minimum run length of 1' and maximum of 25'
- 24V – minimum run length of 1' and maximum of 40'



## INVISILED® CLASSIC SECTIONS

	12V	Qty	24V	Qty	Length	Color	Color Temp	Watt	Lm/ft
Unit	<b>LED-T-2IN</b>	1	<b>LED-T24-2IN</b>	1	2 inch	<b>AM</b> Amber	590-595nm	.33W	22
	<b>LED-T-1</b>	1	<b>LED-T24-1</b>	1	1 foot	<b>BL</b> Blue	465-470nm	2W	20
	<b>LED-T-5</b>	1	<b>LED-T24-5</b>	1	5 feet	<b>GR</b> Green	515-520nm	10W	60
Bulk	<b>LED-T-2IN-10</b>	10	<b>LED-T24-2IN-10</b>	10	2 inch	<b>RD</b> Red	625-630nm	.33W	35
	<b>LED-T-1-25</b>	25	<b>LED-T24-1-40</b>	40	1 foot	<b>WT</b> White	3500K	2W	90

Example Order: **LED-T24-1-BL**

## ACCESSORIES

### CLASS 2 POWER SUPPLY

12V	24V		Watt
<b>EN-1260-RB2-T</b>	<b>EN-2460-RB2-T</b>	Remote	60W
	<b>EN-24100-RB2-T</b>		96W
<b>EN-1260-P-AR-T</b>	<b>EN-2460-P-AR-T</b>	Plug-in	60W
	<b>EN-24100-P-AR-T</b>		96W

Input 120V

A 6' lead wire is included. Minimum load requirement of 1W for consistent operation.

### JOINER CABLE

12V	24V	Length
<b>LED-T-IC2</b>	<b>LED-TC-IC2</b>	2"
<b>LED-T-IC6</b>	<b>LED-TC-IC6</b>	6"
<b>LED-T-IC12</b>	<b>LED-TC-IC12</b>	12"
<b>LED-T-IC72</b>	<b>LED-TC-IC72</b>	72"

Connects two sections of INVISILED®.

### ADDITIONAL LEAD WIRES

12V	24V	Length
<b>LED-T-P-2</b>	N/A	2 ft.
<b>LED-T-P-12</b>	N/A	12 ft.

Alternative length of lead wires for plug-in or remote power supply. May be field cut for use with a remote power supply.

### 4-WAY "X" CONNECTOR

12V	24V
<b>LED-T-X</b>	<b>LED-TC-X</b>

X connector has one male and three female connectors and can be used to easily customize your design layout.

### 3-WAY "Y" CONNECTOR

12V	24V
<b>LED-T-Y</b>	<b>LED-TC-Y</b>

Y connector has one male and two female connectors and can be used to easily customize your design layout.

### L CONNECTOR

12V	24V
<b>LED-T-L</b>	<b>LED-TC-L</b>

L connector has male and female connectors and is used to create 90° right angles.

### END CAP

12V	24V
<b>LED-T-EC</b>	<b>LED-TC-EC</b>

Cut end cap  $\frac{1}{2}$ "L x  $\frac{1}{4}$ "W x  $\frac{3}{16}$ "H

Male end cap  $\frac{1}{2}$ "L x  $\frac{1}{2}$ "W x  $\frac{1}{16}$ "H

Includes 1 cut end cap and 1 male end cap. Use to terminate every run to protect against contaminants.

### MOUNTING CLIPS

<b>LED-T-CL</b>	$\frac{1}{2}$ "
Qty	10

For installation on surfaces that are difficult to adhere to. Two mounting clips per foot are recommended for straight runs.

### RETROFIT CHANNEL

<b>LED-T-RC</b>	36"L x $\frac{1}{2}$ "W x $\frac{1}{2}$ "H
-----------------	--

Use to construct a miniature cove or light baffle in which tape may be concealed. May also be mounted to the channel as a way to change the direction of the projected light.