

# EQ® Load Centers—Circuit Breaker Enclosures

## 1-Phase and 3-Phase, 240V AC Max.

### Features

- Circuit breaker enclosures range from 60A to 225A, indoor and outdoor models
- Designed for use exclusively with QP, QT, QPH, HQP, BQ, BQH, HBQ, QPP, QPPH, HQPP, QJ2, QJH2 and QJ2-H circuit breakers
- UL listed
- Suitable for use as service entrance equipment
- UL listed for 60/75°C conductors (See equipment markings for applications)



| Breaker Used |               |              | Indoor Enclosure — NEMA Type 1 |           |                     |       |       | Outdoor Enclosure — NEMA Type 3R |           |                     |       |       |
|--------------|---------------|--------------|--------------------------------|-----------|---------------------|-------|-------|----------------------------------|-----------|---------------------|-------|-------|
| Frame Type   | Ampere Rating | No. of Poles | Catalog Number                 | Std. Pkg. | Dimensions (inches) |       |       | Catalog Number                   | Std. Pkg. | Dimensions (inches) |       |       |
|              |               |              |                                |           | Height              | Width | Depth |                                  |           | Height              | Width | Depth |

### 1-Phase, 3-Wire SN — 120/240 Volts AC

|                     |     |     |                |   |        |       |        |                |   |        |        |         |
|---------------------|-----|-----|----------------|---|--------|-------|--------|----------------|---|--------|--------|---------|
| QP, QPH, HQP        | 60  | 2   | E0204ML1060S®  | 5 | 9 7/8  | 5 1/8 | 2 5/8  | W0204ML1060®   | 5 | 18     | 15     | 4 1/4   |
|                     | 60  | 2   | E0204ML1060F®  | 5 | 9 7/8  | 5 1/8 | 2 5/8  | —              | — | —      | —      | —       |
|                     | 100 | 2   | E0202MB1100    | 1 | 17 1/8 | 7 3/8 | 4 5/16 | W0202MB1100CU® | 1 | 17.4   | 7.3    | 4.3     |
|                     | 125 | 2   | E0204ML1125SCU | 1 | 17 1/8 | 7 1/8 | 4 1/4  | W0204ML1125CU  | 1 | 17 1/8 | 17 3/8 | 4 5/16  |
| QN, QNH, HQN        | 150 | 2   | —              | — | —      | —     | —      | W0202MB1150CU® | 1 | 19 3/4 | 18.4   | 4.6     |
|                     | 200 | 2   | —              | — | —      | —     | —      | W0202ML1200CU  | 1 | 19 3/4 | 18.4   | 4.6     |
|                     | 200 | 2   | E0202MB1200®   | — | 19 3/8 | 8 1/2 | 4      | W0202MB1200CU® | 1 | 19 3/4 | 18.4   | 4.6     |
| QPP, QPPH, HQPP, QP | 225 | 1-4 | —              | — | —      | —     | —      | W0406ML1225CU® | 1 | 23     | 10     | 4 1/8   |
| QJ2, QJH2, QJ2-H    | 150 | 2   | —              | — | —      | —     | —      | WB2150B®       | 1 | 27     | 17 3/8 | 4 15/16 |
|                     | 200 | 2   | —              | — | —      | —     | —      | WB2200B®       | 1 | 27     | 17 3/8 | 4 15/16 |
|                     | 225 | 2   | —              | — | —      | —     | —      | WB2225®        | 1 | 27     | 17 3/8 | 4 5/16  |

### 3-Phase, 3-Wire 240 Volts AC or 3-Phase, 4-Wire SN — 120/208 Volts AC, 120/240, 240 Volts AC

|                  |     |     |               |   |        |        |       |              |   |        |        |        |
|------------------|-----|-----|---------------|---|--------|--------|-------|--------------|---|--------|--------|--------|
| QP, QPH, HQP     | 100 | 2-3 | E0303ML3100S® | 1 | 17 1/8 | 7 1/8  | 4 1/4 | W0303ML3100® | 1 | 17 1/8 | 17 3/8 | 4 5/16 |
| BQ, BQH, HBQ     | 100 | 2-3 | EB3100S®      | 1 | 17 1/8 | 7 1/8  | 4 1/4 | WB3100®      | 1 | 17 1/8 | 17 3/8 | 4 5/16 |
| QJ2, QJH2, QJ2-H | 225 | 2-3 | EB3225F®      | 1 | 27 1/4 | 10 1/8 | 5 1/8 | WB3225®      | 1 | 27     | 10 1/8 | 5 9/16 |

Ⓢ Will not accommodate 2-pole GFCI or circuit breaker with shunt trip.  
 Ⓢ 42,000A IR maximum. Copper wire only at 225A.

Ⓢ Can accommodate 2-pole GFCI breaker up to 50A. For 2-pole GFCI, a restriction of #6 wire applies due to wire bend space of the enclosure. Will not accommodate circuit breaker with shunt trip.

Ⓢ Main breaker factory installed.  
 Ⓢ QJ2 frame circuit breaker installed, rated 10,000A IR.  
 Ⓢ CSA Listed.