


Lighting Contactors

CR463L

Electrically Held Contactors
CR463L - 30A (2-12 pole)
Standard Assembled Forms

Section 3



Product Number Selection Instructions

Replace * in the product number with the appropriate digits from the Coil Voltage table. The resulting product number will be for an assembled contactor with no additional auxiliary contacts, pilot devices, pilot lights, control circuit fuses or CPTs. There is no list price adder for Coil Selection.

For modified assembled forms with those modifications, see pages 3-11 and 3-12.

- Items listed here are the most common pole configurations.
- Poles may be reconfigured by the user into alternative combinations of NO and NC contacts.
- All configurations are available as factory-assembled forms.

Open

No. of Poles	Contact Configuration	Product Number
2	1NO-1NC	CR463L11A*A
2	2NO	CR463L20A*A
3	3NO	CR463L30A*A
4	3NO-1NC	CR463L31A*A
4	4NO	CR463L40A*A
5	5NO	CR463L50A*A
6	5NO-1NC	CR463L51A*A
6	6NO	CR463L60A*A
7	7NO	CR463L70A*A
7	NO-1NC	CR463L71A*A
8	8NO	CR463L80A*A
9	9NO	CR463L90A*A
10	9NO-1NC	CR463L91A*A
10	10NO	CR463LB0A*A
11	11NO	CR463LC0A*A
12	12NO	CR463LD0A*A

Enclosed NEMA Type 1 Surface Mount

No. of Poles	Contact Configuration	Product Number
2	1NO-1NC	CR463L11A*A10A0
2	2NO	CR463L20A*A10A0
3	3NO	CR463L30A*A10A0
4	3NO-1NC	CR463L31A*A10A0
4	4NO	CR463L40A*A10A0
5	5NO	CR463L50A*A10A0
6	5NO-1NC	CR463L51A*A10A0
6	6NO	CR463L60A*A10A0
7	7NO	CR463L70A*A10A0
8	7NO-1NC	CR463L71A*A10A0
8	8NO	CR463L80A*A10A0
9	9NO	CR463L90A*A10A0
10	9NO-1NC	CR463L91A*A10A0
10	10NO	CR463LB0A*A10A0
11	11NO	CR463LC0A*A10A0
12	12NO	CR463LD0A*A10A0

Enclosed NEMA Type 1 Surface Mount (Oversize)¹

No. of Poles	Contact Configuration	Product Number
2	1NO-1NC	CR463L11A*A10AA
2	2NO	CR463L20A*A10AA
3	3NO	CR463L30A*A10AA
4	3NO-1NC	CR463L31A*A10AA
4	4NO	CR463L40A*A10AA
5	5NO	CR463L50A*A10AA
6	5NO-1NC	CR463L51A*A10AA
6	6NO	CR463L60A*A10AA
7	7NO	CR463L70A*A10AA
8	7NO-1NC	CR463L71A*A10AA
8	8NO	CR463L80A*A10AA
9	9NO	CR463L90A*A10AA
10	9NO-1NC	CR463L91A*A10AA
10	10NO	CR463LB0A*A10AA
11	11NO	CR463LC0A*A10AA
12	12NO	CR463LD0A*A10AA

¹Oversize enclosures required for field installed pilot devices, pilot lights and controls power transformers.

Enclosed NEMA Type 1 Flush Mount

No. of Poles	Contact Configuration	Product Number
2	1NO-1NC	CR463L11A*A80A0
2	2NO	CR463L20A*A80A0
3	3NO	CR463L30A*A80A0
4	3NO-1NC	CR463L31A*A80A0
4	4NO	CR463L40A*A80A0
5	5NO	CR463L50A*A80A0
6	5NO-1NC	CR463L51A*A80A0
6	6NO	CR463L60A*A80A0
7	7NO	CR463L70A*A80A0
8	7NO-1NC	CR463L71A*A80A0
8	8NO	CR463L80A*A80A0
9	9NO	CR463L90A*A80A0
10	9NO-1NC	CR463L91A*A80A0
10	10NO	CR463LB0A*A80A0
11	11NO	CR463LC0A*A80A0
12	12NO	CR463LD0A*A80A0

Coil Voltage

Insert coil digit in place of * in digit 10.

Coil Voltage	AC, 50Hz	Coil Digit
AC, 60Hz		
24V	20V	C
28V	24V	D
115-120V	110V	J
200-208V	—	L
230-240V	220V	S
277V	240V	N
347V	—	T
460-480V	440V	U
575-600V	550V	Y

