

Ordering information

1AC 230V

Rated data						
P _{rated} (HO)		I _n	Part number	Fans	Frame size	
kW	hp	A				
0.12	1/6	0.9	6SL3210-5BB11-2	V0	–	FSA
0.25	1/3	1.7	6SL3210-5BB12-5	V0	–	
0.37	1/2	2.3	6SL3210-5BB13-7	V0	–	
0.55	3/4	3.2	6SL3210-5BB15-5	V0	–	
0.75	3/4	3.9	6SL3210-5BB17-5	V0	–	
0.75	1	4.2	6SL3210-5BB18-0	V0	1	FSB
1.1	1–1/2	6	6SL3210-5BB21-1	V0	1	
1.5	2	7.8	6SL3210-5BB21-5	V0	1	FSC
2.2	3	11	6SL3210-5BB22-2	V0	1	
3	4	13.6	6SL3210-5BB23-0	V0	1	

EMC Standards

With integrated line filter category C2 ⁶⁾	A
Without integrated filter	U

1AC 230V options

FS	P _{rated} (HO) kW	Braking resistor 6SE6400-...	Line reactor 6SE6400-...	Output reactor 6SE6400-...	Shield connection kit 6SL3266-...	Line filter class B ³⁾ 6SE6400-...	Corresponding to the IEC standard		
							Standard fuse ⁴⁾		Circuit breaker ⁴⁾
							Current in A	Part number	Part number
A	0.12	4BC05-0AA0	3CC00-4AB3	3TC00-4AD3	1AA00-0VA0	2FL01-0AB0	10	3NA3803	3RV2011-1DA10
	0.25						10	3NA3803	3RV2011-1FA10
	0.37		3CC01-0AB3				10	3NA3803	3RV2011-1HA10
	0.55						10	3NA3803	3RV2011-1JA10
	0.75						16	3NA3805	3RV2011-1KA10
B	1.1	4BC11-2BA0	3CC02-6BB3	3TC01-0BD3	1AB00-0VA0	–	20	3NA3807	3RV2021-4BA10
	1.5						32	3NA3812	3RV2021-4CA10
C	2.2	4BC12-5CA0	3CC03-5CB3	3TC03-2CD3	1AC00-0VA0	–	35	3NA3814	3RV2021-4EA10
	3						50	3NA3820	3RV1031-4FA10

Accessories

Name	Part number
Parameter loader	6SL3255-0VE00-0UA0
BOP (Basic Operator Panel) interface	6SL3255-0VA00-2AA0
Braking module ▪ 1AC 230V: 8A ▪ 3AC 400V: 7A	6SL3201-2AD20-8VA0
V20 BOP (Basic Operator Panel)	6SL3255-0VA00-4BA0
BOP cable 3 m incl. 4 mounting screws	6SL3256-0VP00-0VA0
SINAMICS Memory Card (SD) 512 MB	6SL3054-4AG00-2AA0
RS485 Terminators (50 pieces)	6SL3255-0VC00-0HA0
SINAMICS V20 training case	6AG1067-2AA00-0AB6
DIN Rail mounting kit	FSA: 6SL3261-1BA00-0AA0 ⁵⁾ FSB: 6SL3261-1BB00-0AA0

Spare parts

Replacement fan	
Frame size	Part number
FSA	6SL3200-0UF01-0AA0
FSB	6SL3200-0UF02-0AA0
FSC	6SL3200-0UF03-0AA0
FSD	6SL3200-0UF04-0AA0
FSE	6SL3200-0UF05-0AA0