



Meter Centers

Lever Bypass, Over/Under Meter-Load Center Combo, 1-Phase, 3-Wire 120/240V AC

METER CENTERS 2

- UL listed
- Talon HQ lever bypass (heavy duty)
- 125-200 amp
- Overhead and underground feed applications
- Load wires bottom or back exit only
- 22,000 AIC rated, or as noted
- Pad locking provisions on all devices
- Side hinge doors removable by backing out only one screw
- Suitable for use only as service entrance equipment
- Contact local utility to confirm meter socket placement prior to installation
- See end of section for dimensions and wiring diagrams
- See page 2-42 for Solar Ready lever bypass
- See page 2-44 for 300-400A lever bypass

MC2040B1200JLC



200A meter load center with lever bypass

Meter Combinations

Catalog Number	Amp Rating (Cont.)	Utility Incoming	Bypass Type	No. of Spaces	No. of Circuits	Dimensions (inches)			Main Breaker	Short Circuit Rating	Hub Provision	5th Jaw	Cover Type
						H	W	D					

Meter-Load Center Combination, 125-200amp, Lever Bypass^①

MC0408B1200JLT	200	OH/UG	Lever	4	8	30.5	16.0	5.0	EQ9985	22,000	RX	Installed	Ringless
MC0816B1150JLT ^②	150		HQ	8	16	32.1	14.3	5.2	MBK150				
MC0816B1200JLT ^②	200		Lever Bypass	12	24				MBK200				
MC1224B1125JLC	125		MBK125										
MC1224B1200JLC	200		MBK200										
MC2040B1150JLC	150	OH/UG	HQ	20	40	36.1	14.3	5.2	MBK150	RX-top, HC-bot	Installed	Ringless	
MC2040B1200JLC	200		Lever Bypass	30	42	42.1			MBK200				
MC3042B1200JLC													

^① Due to wire space restrictions on the trough side, the left side of the interior is limited to a 60A max branch.

^② Feed thru lugs included.