

17" Vacu-Break Accessories

Accessories 240V AC Vacu-Break 17" Panel

Vacu-Break Catalog Number	Depth Extension Kit	J-Fuse Adaptor Kit ①	R-Fuse Adaptor Kit ①	T-Fuse Adaptor Kit ②	Number and Ranges Lugs Per Pole (Cu/Al)
V7A2211	W48762	—	—	—	1 PC. #14 To #8
V7A3211	W48762	—	—	—	1 PC. #14 To #8
V7B2211	W48763	③	—	—	1 PC. #14 To #4
V7B3211	W48763	③	—	—	1 PC. #14 To #4
V7B3211R	W48763	—	Factory Installed	—	1 PC. #14 To #4
V7B2212	W48763	③	—	—	1 PC. #14 To #2
V7B3212	W48763	③	—	—	1 PC. #14 To #2
V7B3212R	W48763	—	Factory Installed	—	1 PC. #14 To #2
V7B2222	W48763	③	—	—	1 PC. #14 To #2
V7B3222	W48763	③	—	—	1 PC. #14 To #2
V7B3222R	W48763	—	Factory Installed	—	1 PC. #14 To #2
V7E3223	W48764	W49827-100A W49829-60A	W55365-100A W56628-60A	TFAK32-100A —	1 PC. #10 To #1/0 1 PC. #14 To #1/0
V7E2223	W48764	W49827-100A W49829-60A	W55365-100A W56628-60A	TFAK32-100A —	1 PC. #12 To #1/0 1 PC. #14 To #1/0
V7E2233	W48764	W49827	W55365	TFAK32	1 PC. #12 To #1/0
V7E3233 & V7E3233R	W48764	W49827	W55365 ④	TFAK32	1 PC. #10 To #1/0
V7F3644 & V7F3244R	W48765	—	W55366 ⑤	TFAK42	1 PC. #6 To 250kcmil
V7E2204	W48764	W49819	W55366	TFAK42	1 PC. #6 To 250kcmil
V7F3204	W48765	W49819	W55366	TFAK42	1 PC. #6 To 250kcmil
V7H2205	—	W49814	W55367	TFAK52	1 PC. #1/0 To 500kcmil
V7H3205	—	W49814	W55367	TFAK52	1 PC. #1/0 To 500kcmil
V7H3205750	—	W49814	W55367	TFAK52	1 PC. 250-750kcmil
V7H2206	—	W49813	W55368	TFAK62	2 PC. #4/0 To 500kcmil
V7H3206	—	W49813	W55368	TFAK62	2 PC. #4/0 To 500kcmil
V7F3203MS	W48764	W49827	W55365	TFAK32	Supplied w/CU pads
V7F3204MS	W48765	W49819	W55366	TFAK42	Supplied w/CU pads
V7F3205MS	—	W49814	W55367	TFAK52	Supplied w/CU pads
V7F3206MS	—	W49813	W55368	TFAK62	Supplied w/CU pads

W48762, W48763, W48764, W48765 Hardware to extend unit depth from 6.75 to 10.50 inches.

① Double branch units require 2 kits per unit.

② "T" fuse adaptor kit includes hardware for 1 pole only.

③ For 240V AC "J" Fuse application, use 600V AC unit and appropriate 240V AC "J" Fuse kit 30A Unit - W49831; 60A Unit - W49829.

④ Factory installed in V7E3233R.

⑤ Factory installed in V7F3244R.

Vacu-Break Connecting Strap Kits For Panelboards and Switchboards

Ampere Rating	240V Unit Height (Inches)	600V Unit Height (Inches)	S4/F1, FPP (10" Deep) Strap Kit	S5/F2, FPP (12.75" Deep) Strap Kit	SB1, SB2, SB3, FC-20, FC-1 VB-5, VB-6 Strap Kit
30-30	2.50	—	F602	F602D	—
30-30	5	7.50	F657	F657D	VB657
30-60	5	7.50	F657	F657D	VB657
60-60	5	7.50	F657	F657D	VB657
60-100	7.50	7.50	F657	F657D	VB657
100-100	7.50	7.50	F657	F657D	VB657
100	7.50	7.50	F657	F657D	VB657
200	7.50, 10	7.50, 10	F671	F671D	VB671
200-200	10	10	F672	F672D	VB672
400	15	15	F6150	F6150D	VB6150
600	15	15	F6150	F6150D	VB6150