


ELA-75-BF

ELECTRONIC TRANSFORMER



LET 75 BF



HEAVY DUTY 12V 75W AC BOTTOM FEED TRANSFORMER

L: 2-3/8"

W: 1-1/4"

H: 7/8"

DESCRIPTION:

This quiet 75W-12V bottom feed electronic step-down transformer is designed to be used with low voltage lighting systems and is protected against overload, short circuit and over heat and has a 4 year guarantee.

TECHNICAL SPECIFICATIONS

INPUT	120V 60Hz
OUTPUT AT MAX. LOAD	11.7V 40kHz
MAXIMUM LOAD	75W
MINIMUM LOAD W/O DIMMER	10W
MINIMUM LOAD WITH DIMMER	20W
OUTPUT CURRENT AT MAXIMUM LOAD	6.35A
POWER FACTOR MIN.	0.95
DIMMABLE	✓
WATER-PROOF POTTING	✓
ALUMINUM CASING	✓

SPECIFIED BY:

TYPE:

JOB NAME:

elite LIGHTING U.S.A.

Tel: 323-888-1973 • 877-375-5555 / Fax: 323-888-1977 • 877-375-3333
www.iuseelite.com • E-mail: sales@iuseelite.com